

Instruction of Additel 761 Upgrade Wizard

V1.0

7/3/2015

Warning:

- Please use automatic upgrade first. Only use upgrade wizard in some special cases (ex: Not found the local service package in automatic upgrade process).
- The Upgrade wizard be used must be in our guidance.

Step1.

Click the menu “**Tool-> Upgrade Wizard**”, show dialog as follows:




Figure 1

Step2.

Click [**OK**], the Firmware Upgrade dialog is displayed (**show as Figure 2**).




Figure 2

Step3.

Click [??] of the Name under Local Service Package, select the “OS” folder (show as figure 3):




Figure 3

Open the "OS" folder, select the proper firmware file and click "open" button to return to the Update dialog (show as figure 4).

Note:

If you are not sure the proper firmware file that the instrument can be used, please check the system information of the instrument first. You can go to "Setup" -> "Information" -> "Sys Info" on the instrument to view the software version, hardware version and serial number, and then contact us (www.additel.com), we will tell you the proper firmware file for the instrument.




Figure 4

Step4.

Click [[Load](#)] button to start upgrade firmware and languages etc.

Warning:

- It is important not to interrupt the updating process. This may cause the upgrade to fail, which will cause the instrument does not work.

Step5.

When all the upgrade is completed, you will see the tip in the upgrading log box (shown as Figure 5).




Figure 5